

TECHNIRADIO 8

Portable DAB+ / FM radio with voice announcements

EAN	Colour	ltem no.	Weight (Box)	Weight	Вох	Device (W x H x D)
4019588039308	schwarz/silber	0000/3930	1.37 kg	900 g	33.00 x 21.50 x 13.00 cm	26.00 x 21.10 x 10.00 cm

TOP FEATURES

DAB+ digital radio	Date and time display	Electronic volume control Mains and battery operated
FM radio (with RDS and PLL)	Snooze and sleep functions	
Favorites memory slots (3 DAB+/3 FM)	Voice announcements (main functions and	
Backlit LC display	pressed keys are announced by voice)	
	Adjustable equalizer	

AMBIENT OPERATING CONDITIONS	Sleep timer: Y	
Humidity: 5 - 90 % relative air humidity (non-	Snooze: Yes	
condensing)	Favourites pre	
Ambient temperature: 5 - 35 °C	Favourites pr	
CONNECTIONS	LOUDSPEAKE	
USB: 1	Mono speake	
Headphone connection jack (3,5mm): 1	Stereo speake	
DISPLAY	Output perfo	
Dimmable: Yes	Stereo: 2 x 3 \	
Type: LCD	OTHER FEATU	
FUNCTIONS	OSD language	
MP3 playback via USB: Yes	Italian, Dutch	
HANDLING/COMFORT	POWER CONS	
Clock: Yes	In operation:	
Automatic time reset following a power cut:	Standby: 0,3 \	
Yes	POWER SUPP	
Alarm: Yes		

Sleep timer: Yes	Nominal voltage: 230 V Frequency: 50 Hz Mains adapter: DC 6 V / 1,000 mA		
Snooze: Yes			
Favourites programme manager FM: 3			
Favourites programme manager DAB+: 3	Non rechargeable battery: 4x AA LR6 type		
LOUDSPEAKERS	(not included with delivery)		
Mono speakers: Yes	Type of power supply: External		
Stereo speakers: Yes	RADIO / RECEPTION		
Output performance: 6 W (RMS)	DAB+: 174 - 240 MHz FM/RDS: 87.5 - 108 MHz Aerial: Telescopic antenna		
Stereo: 2 x 3 W			
OTHER FEATURES			
OSD languages: English, German, French,	RADIO TYPE		
Italian, Dutch, Norwegian	Pocket radio: Yes		
POWER CONSUMPTION	stationary radio: Yes		
In operation: 6 W	SCOPE OF DELIVERY		
Standby: 0,3 W	TECHNIRADIO 8, plug-in power supply, instruction manual		
POWER SUPPLY			

TechniSat