



The Button FGPB-101-1 ZW5 – FGPB-101-8 ZW5

Colour options:



Product Overview:

FIBARO Button is a compact, battery-powered, Z-Wave Plus compatible device. It allows you to control devices through the Z-Wave network and run various scenes defined in FIBARO System.

Different actions may be triggered with one to five clicks or by holding the button down. In panic mode, each press of the button results in triggering of the emergency scene.

With its small design and wireless communication, the FIBARO Button can be conveniently mounted on any surface and in any position or location at home, e.g. beside the bed or under the desk.

Main features:

- Compatible with any Z-Wave or Z-Wave+ Controller,
- Supports protected mode (Z-Wave network security mode) with AES-128 encryption,
- Completely wireless with battery power and Z-Wave communication,
- May be installed anywhere in your home,
- Extremely easy installation - simply add and put on desired surface,
- Many colour variations: white, black, red, yellow, green, blue, brown and orange.



The Button FGPB-101-1 ZW5 – FGPB-101-8 ZW5

Technical Data:

- Battery type: ER14250 1/2AA 3.6V
- Battery life: est. 2 years (with default settings and max. 10 pushes per day)
- Operating temperature: 0 - 40°C
- EU standards compliance: EMC 2014/30/EU, RED 2014/53/EU, RoHS 2011/65/EU, LVD 2014/35/EU
- Radio protocol: Z-Wave (500 series chip)
- Radio frequency: 868.4 or 869.8 MHz EU; 908.4 or 916.0 MHz US; 921.4 or 919.8 MHz ANZ; 869.0 MHz RU;
- Range: up to 50m outdoors, up to 40m indoors
(Depending on terrain and building structure)
- Dimensions (diameter x height): 46 x 34 mm